

MPX-400MIC



Microphone with zone selector for paging and chimes for audio matrix mod. MPX-4088. Selection of 1 to 32 zones. Connection to system using RJ-45, Cat 5e cable.

MICROPHONE	Electret condenser with gooseneck and LED ring
INPUTS	1 balanced mic., XLR 6,800 Ohm 1 mini USB port for loading chimes in MP3 or WAV format 1 RD port for connection to MPX-4088 matrix, RJ-45
CONTROLS	Microphone and zone selector control
CONNECTION	RJ-45, Cat 5e cable
PHANTOM	12 V
POWER SUPPLY	24 V DC, 100 mA, through RD port
DIMENSIONS	Microphone with gooseneck: 430 mm height Base: 176 x 53 x 166 mm depth
WEIGHT	0.86 kg
ACCESSORIES	Foam windshield